COMMERCIAL PA · WALL SPEAKER

# SK-61S

## 6" two-way wall speaker

A 6" two-way wall speaker with taps up to 40 W or 8 Ω, for bars, lounges, gyms and halls that need fuller sound.

6" + 1" two-way | 5–40 W taps | 70 / 100 V or 8 Ω | White or black



**40 W**
Rated power

**101 dB**
SPL at 20 W

**70 Hz–20 kHz**
Frequency response

**3.34 kg**
Net weight

## More bass from the wall. For bars, lounges and gyms.

The SK-61S steps up to a 6" PP woofer and 1" silk tweeter for fuller music and more level. Four taps up to 40 W on a 70 V or 100 V line, or 8 Ω direct, make it a good fit for bars, lounges, gyms and multipurpose halls.

**Two-way 6"**
6" PP woofer and 1" silk tweeter.

**Up to 40 W**
5 / 10 / 20 / 40 W at 70 V or 100 V, plus 8 Ω.

**Fuller bass**
70 Hz – 20 kHz with 101 dB SPL at 20 W.

**Wall bracket**
Mounts on walls and pillars, angled to the room.

**Robust cabinet**
HIPS housing with a powder-coated metal grille.

**White or black**
Finish to suit the room.

APPLICATIONS

Bars | Lounges | Gyms | Halls | Restaurants | Retail stores

**Skyco Technologies (Pty) Ltd** · 151 Lechwe Street, Corporate Park South, Randjespark, Midrand
+27 11 026 7018 · sales@skycotech.co.za · skycotech.co.za

# Specifications. Every tap, rating and dimension.

### ACOUSTIC

| | |
|---|---|
| Drivers | 6" PP woofer + 1" silk tweeter |
| Rated power | 40 W |
| Power taps | 5 / 10 / 20 / 40 W |
| Sensitivity (1 W / 1 m) | 88 ±3 dB |
| SPL | 101 dB at 20 W (100 V) |
| Frequency response | 70 Hz – 20 kHz |

### ELECTRICAL

| | |
|---|---|
| Line voltage | 70 V / 100 V |
| Low impedance | 8 Ω |

### PHYSICAL

| | |
|---|---|
| Housing | HIPS |
| Grille | Powder-coated metal |
| Colour | White or black |
| Dimensions (W × H × D) | 215 × 190 × 284 mm |
| Net weight | 3.34 kg |

### WORKS WITH

| | |
|---|---|
| Smaller rooms | SK-41S 4" wall speaker |
| Volume control | SK-860K |
| Amplifier | T-4120UC, T-4240UC |

Specifications are typical values and may change without notice. Skyco confirms the final configuration with your quote.

## Talk to our audio team.

We design the zones, size speakers and amplifiers to 100 V line practice, supply the system and support it.

1. **Design the zones**
2. **Quote**
3. **Supply**
4. **Install**
5. **Support**

**Skyco Technologies (Pty) Ltd** · 151 Lechwe Street, Corporate Park South, Randjespark, Midrand
+27 11 026 7018 · sales@skycotech.co.za · skycotech.co.za